

Welcome to SimpleWare Digital Media Services 1.2 Device Driver Software

UPGRADING WIRELESS USB NETWORK DEVICE DRIVER

For information on system requirements, installing, and launching SimpleWare 1.2, please read *Section 3, Installation* in your *User Guide*.

This document describes how to upgrade the wireless USB network device driver on Windows XP (the following procedure is similar for all of the supported operating systems - Windows 98SE, ME, 2000, and XP). To upgrade the device driver software:

- (1) Unzip file WDRIVER1.2.ZIP onto a floppy diskette.
- (2) Open the **Start** menu on your PC and select **Settings >> Control Panel**.
- (3) Click on the **Network and Internet Connections** icon.
- (4) Click on the **Network Connections** icon.
- (5) Double-click on the icon for the *Wireless Network Adapter*.
- (6) Click the **Properties** button.
- (7) Click the **Configure** button.
- (8) Click **Driver** tab. Then, click **Update driver** button.
- (9) Select **Install from a list or specific location (Advanced)** and click **Next** button.
- (10) Select **Don't search. I will choose the driver to install** and click **Next** button.
- (11) Click **Have Disk** and browse to the diskette drive containing the contents of WDRIVER1.2.ZIP. If you unzipped these files in another directory, browse to that directory. Then, click **Next** button.
- (12) Follow the instructions in the dialog boxes. When the new driver software for the USB wireless network adapter is installed, restart your PC.

Additional Instructions for SimpleWare 1.0, 1.1, and 1.11 Users

Upgrading your USB network device driver to this version modifies the adapter's **Network Id** to "simple". If you were running SimpleWare 1.0 to 1.11, you will need to reset the **Network Id** to the last three digits of the SimpleFi serial number, reset and rediscover your SimpleFi. For information on setting the **Network Id**, see *Appendix E* of your *SimpleWare 1.0 to 1.11 User Guide*. For information on resetting your SimpleFi, see pages 63 to 64 in *Appendix C* of the *SimpleWare 1.0 to 1.11 User Guide*. For information on rediscovering your SimpleFi, see page 18 of the *SimpleWare 1.0 to 1.11 User Guide*.

Now, download SimpleWare 1.2 from the Motorola SimpleFi Web site (www.simplefi.com). Install SimpleWare 1.2 over your existing SimpleWare 1.0 to 1.11 software, and rediscover your SimpleFi. SimpleWare 1.2 will then upgrade firmware running on SimpleFi.

Additional Instructions for SimpleWare 1.2 Users

Upgrading your USB network device driver to this version modifies the adapter's **Network Id** to "simple".

If your SimpleFi has already been upgraded to 1.2 firmware, your SimpleFi defaults to **Network Id** "simple", and you do not need to change your **Network Id**. If you changed your SimpleFi **Network Id** earlier, reset it to "simple". For information on setting the SimpleFi **Network Id**, see page 57 in the *SimpleWare 1.2 User Guide* (SimpleFi 1.0 to 1.11 users cannot set the SimpleFi **Network Id**).

If your SimpleFi has not been upgraded to 1.2 firmware, install SimpleWare 1.2 software and follow the procedure for SimpleWare 1.0 to 1.11 Users above. If your SimpleFi has been upgraded to 1.2 firmware, follow the discovery procedure described in either *User Guide*.

NOTICES

© 2002 SimpleDevices, Inc. All rights reserved. Used by permission.

Copyright © 2002 by Motorola, Inc.

simplefi User Guide for Windows®

All rights reserved.

No part of this publication may be reproduced in any form or by any means or used to make any derivative work (such as translation, transformation or adaptation) without written permission from Motorola, Inc. or SimpleDevices, Inc.

Any audio content that you may want to play on your simplefi may be protected under copyright law. The unauthorized duplication or sharing of such could be a violation of the rights of the copyright owner. Please be sure to obtain any permission required from the copyright owner.

SimpleDevices, Inc. reserves the right to revise this publication and to make changes in content from time to time without obligation on the part of SimpleDevices, Inc. to provide notification of such revision or change.

SimpleDevices, Inc. assumes no responsibility or liability for any errors or inaccuracies that may appear in this documentation. SimpleDevices, Inc. provides this guide without warranty of any kind, either implied or expressed, including, but not limited, to the implied warranties of merchantability and fitness for a particular purpose. SimpleDevices, Inc. may make improvements or changes in the product(s) described in this manual at any time.

Motorola, Inc. reserves the right to revise this publication and to make changes in content from time to time without obligation on the part of Motorola Inc. to provide notification of such revision or change.

Motorola, Inc. assumes no responsibility or liability for any errors or inaccuracies that may appear in this documentation. Motorola, Inc. provides this guide without warranty of any kind, either implied or expressed, including, but not limited, to the implied warranties of merchantability and fitness for a particular purpose. Motorola Inc. may make improvements or changes in the product(s) described in this manual at any time.

Acrobat® Reader Software is provided subject to the Adobe Systems, Inc. Software End User License Agreement included

on the CD-ROM. Acrobat is a registered trademark of Adobe Systems, Inc. in the United States and/or other countries. Acrobat Reader 4.0 © 1987-1999 Adobe Systems Incorporated. All rights reserved. simplefi, SimpleWare, SimpleServe, Media Manager, SimpleServe Console, and Online Guide are either registered trademarks or trademarks of SimpleDevices Incorporated in the United States and/or other countries. MOTOROLA and the stylized M logo are registered trademarks of Motorola, Inc. © U.S. Patent and Trademark Office All other product or service marks are the property of their respective owners.

OTHER NOTICES

For other notices, review file README.WRI and NOTICES.WRI.
